## BM-16DB

#### Active Broadcast Media Mult Box

BM16DB109-1



#### **FEATURES**

- Mic/line switchable input
- 16 isolated mic/line switchable outputs
- Jensen® transformers
- Level control
- XLR, 1/4" phone, RCA and mini outputs
- VU output level meter
- Active electronics
- AC or battery powered

- Professional signal levels
- High signal to noise ratio
- Professional quality construction
- Compact size (14H x 18W x 5D inches)
- Rugged Zero Haliburton aluminum case
- 220 V European adapter available
- Rack or wall mount versions available
- Made in the USA

The RCI **BM-16DB** is a 16 output portable active Broadcast Media Mult Box, designed with the needs of the professional news, conference and production organization in mind. The BM-16DB enables a single mic or line level audio source to feed 16 mic/line switchable outputs.

The balanced input of the BM-16DB is mic/line switchable and designed to operate with the line feed from a mixer or directly with a microphone. Phantom power is switched on in the mic position. A level control and VU meter provide the means for setting proper output level, adjusting for various source levels. The 16 balanced XLR outputs are mic/line switchable. Additionally, 1/4" phone, RCA and mini outputs are provided on four of the sixteen outputs for unbalanced equipment. The outputs are highly isolated to prevent problems in equipment connected to one feed from affecting the other feeds. Multiple BM-16DB's can be linked together via the link output XLR.

The BM-16DB is powered by 120 VAC 60 Hz. Alternately, it may also be powered by four 9V batteries (approximately 2 1/2 hours at full load with fresh alkaline batteries). The batteries serve as a backup power source when used with standard AC power, automatically going into battery backup under power failure.

Designed for professional broadcast industry use, the BM-16DB utilizes high performance Jensen® transformers. Housed in a rugged Zero Haliburton aluminum case. 220 V. European adapter available. (Model # XXXXX)

Rack mount (BM-16DBRM), surface wall mount (BM-16DBSM), and flush wall mount (BM-16DBFM) versions also available. Note: Rack mount and wall mount versions do not include battery section and standard color is black anodize. Custom configurations and colors available.



## BM-16DB

#### Active Broadcast Media Mult Box

BM16DB109-1

### **SPECIFICATIONS:**

Input: Mic/line switchable

Mic Input: -46dBu transformer balanced, 1.2k ohm, -72dBu sensitivity, 18VDC phantom

Line Input: +4dBu transformer balanced, 20k ohm, -20dBu sensitivity

Link Output: +4dBu transformer balanced, 600 ohm

Output: Mic/line switchable

Mic Output: -46dBu transformer balanced, 150 ohm

XL Line Output: +4dBu transformer balanced, 600 ohm, +23dBu clip

Unbalanced Line Output: -20dBV unbalanced, 600 ohm

Frequency Response: 20Hz - 20kHz, +0.5dB

THD: Less than .01% Noise: 75 dB signal to noise

Output Isolation: 120dB mic to mic/line, 80dB line to mic/line

Dimensions: 355 mmH x 457 mmW x 127 mmD (14" x 18" x 5")

Weight: 7.3 Kg (16 lbs.)

Power: 110 VAC, 60 Hz or 4-9V batteries

Finish: Clear anodize

# A & E SPECIFICATIONS